Hydro One Networks Inc.
255 Matheson Blvd West
Mississauga, Ontario
L5R 3G3

AMIO
RetailMeterTechServices@HydroOne.com

The latest version of the "CSA-Approved Meter-Mounting Devices" which is located on the Hydro One website will be considered acceptable. Meter-Mounting Device models not listed in this document, may be installed on the condition the model complies with the "Meter-Mounting Device (MMD) Requirements" listed below. The models provided in this document are examples that are known to comply with the Hydro One requirement. Any deviation from this list of requirements must be approved by Hydro One prior to installation. Failure to install a Meter-Mounting Device as described in this document may result in the refusal to connect the service. Refer to the Hydro One Retail Metering Guide for additional information.

Meter-Mounting Device (MMD) Requirements

All Meter-Mounting Devices (MMDs) must meet these requirements:

No.	Requirement
1.	MMD must be approved to CSA C22.2 No.115
2.	MMD with Transfer Switch must be approved to CSA C22.2 No.178.1
3.	MMD with Load Centre must be approved to CSA C22.2 No.29 or No.229
4.	Meter-Centre must be approved to CSA C22.2 No.229
5.	Accommodate meter ring or means to secure meter in place with tamper-proof seal.
6.	Self-Contained MMDs less than 347/600V must be free of obstructions that hinder the ability for the meter to communicate consistently over the AMI network or hinder access to maintain the meter such as covers, cloaks, plates, or padlocks.
7.	Transformer-Rated MMDs must have a test switch, no automatic by-pass or shorting circuit.
8.	Transformer-Rated 3S MMDs must prevent meter removal without shorting the CT.
9.	MMD must have isolated neutral per latest OESC Bulletin 10-15-*
Notes	1. Unless certified by the OEM using OEM equipment, field modification or alterations (e.g. drilled holes, altered lug connector) to the MMD are not permitted unless approved by Hydro One. 2. MMD shall only be used for its intended purpose and shall not be used as a junction box, trough, or raceway.

Additionally, if Hydro One owns underground cable and is accountable for line side cable connection in MMD the following also applies:

No.	Requirement
1.	For Single-Position, oversized MMD with a minimum dimension of 17 H x 12 W x 4 ¾ D inch (432 x 305 x 121mm).
2.	Space above line side connection shall accommodate a half-loop (180 degrees) of extra cable length for frost loop and reconnection while maintaining cable bending radius. See RMG Appendix B.
3.	2-inch conduit knock-out when 3/0 service cable installed (single-phase service, 120/240V).
4.	3-inch conduit knock-out when 250MCM service cable is installed (single-phase service, 120/240V).
5.	Multi-Position models must have a blank compartment for cable entrance.
6.	Models with 400A main shall accommodate parallel 3-inch conduit knock-outs for service cables.

The following list of Meter-Mounting Devices (MMDs) are examples that meet the requirements set by Hydro One:

For single phase overhead connections, the demarcation point is typically at the top of the Customer's service entrance stack.

Single Phase, Three-Wire Service, Self-Contained

120/240V 4-Jaw ANSI Form Factor 2S

SERVICE & TYPE	MANUFACTURER	MODEL	CONDUCTOR SIZE
200A Overhead/Underground	Hydel	EK400ROHO	No.6 – 250MCM Cu/Al
		EK400ROBC	No.6 – 250MCM Cu/Al
		EK200XL	No. 2 – 350MCM Cu/Al
	Microlectric®	BS2-INTCVBC	No.6 – 250MCM Cu/Al
	Eaton	LMB3-IN	No.6 – 250 MCM Cu/Al

120/240V 4-Jaw ANSI Form Factor 2S with Breaker

SERVICE & TYPE	MANUFACTURER	MODEL	CONDUCTOR SIZE
200A Overhead/Underground	Hydel	JA402R-BC	No.6 – 250MCM Cu/Al
		JA402-BC-HI	No.6 – 250MCM Cu/Al
	Eaton	RCJ2Q Series	No.6 – 250MCM Cu/Al
	Durham[2]	DR Series	No.6 – 250MCM Cu/Al
	Microlectric®	CO2-GBC Series	No.6 – 250MCM Cu/Al

120/240V 4-Jaw ANSI Form Factor 2S Specialty Base

SERVICE & TYPE	MANUFACTURER	MODEL	CONDUCTOR SIZE
Up to 200A Combination Base and Load-Centre Service	Leviton	LS800-BRC Series	No.6 – 350MCM Cu/Al
	Eaton	RCPM Series	No.6 – 250MCM Cu/Al
100A or 200A Combination Base with Auto Transfer Switch	Eaton	EGS Series	No.6 – 250MCM Cu/Al
100A or 200A Combination Base with Manual Transfer Switch	Eaton	RCJ Series	No.6 – 250MCM Cu/Al
	Durham[2]	SB Series	No.6 – 250MCM Cu/Al
100A or 200A Overhead/Underground with Load Side Sub Feed Lug	Eaton	LMB3-IN-SF	No.6 – 250MCM Cu/Al
	Hydel	SLC402RW	No.6 – 250MCM Cu/Al

[2]Contact Jesstec Industries Inc to order

120/240V 4-Jaw ANSI Form Factor 2S – Multi-Position

SERVICE & TYPE	MANUFACTURER	MODEL	CONDUCTOR SIZE
200A Main 100A per position Underground	Hydel	MCC200TW-S Series	No.6 – 250MCM Cu/Al
	Microlectric®	BEC (-VE preferred) Series with IN4000 Series Kit	No.6 – 250MCM Cu/Al
200A Main 100A per position Underground with Breaker	Hydel	JAU200 Series	No.6 – 250MCM Cu/Al
		JAL200 Series	
200A Main 200A per position Overhead/Underground	Hydel	HC20 Series	No.6 – 250MCM Cu/Al
	Eaton	K2-IN Series	No.6 – 250MCM Cu/Al
	Microlectric®	BDA2-V Series with IN4000-3 Kit	No.6 – 250MCM Cu/Al
200A Main 200A per position Underground	Hydel	MSC20 Series	No.6 – 250MCM Cu/Al
	Eaton	KU2CLX-IN Series	No.6 – 250MCM Cu/Al
	Microlectric®	BDC Series with IN4000 Series Kit	No.6 – 250MCM Cu/Al
200A Main 200A per position Underground with Breaker	Hydel	JAU20 Series	No.6 – 250MCM Cu/Al
		JAL20 Series	
400A Main 200A per position Underground	Hydel	MSC800TW Series	No.2 – 600MCM Cu/Al
			2 x 1/0-250MCM Cu/Al
400A Main 200A per position Underground with Breaker[3]	Hydel	JAU40RX Series	No.2 – 600MCM Cu/Al
			2 x 1/0-250MCM Cu/Al
Meter-Centre >400A Main or more than 6 positions	Schneider Electric	Square D Series	

Single Phase, Three-Wire Service, Transformer-Rated

120/240 5-Jaw ANSI Form Factor 3S

SERVICE & TYPE	MANUFACTURER	MODEL
400A *Must specify with vendor at time of order* 1. Overhead or Underground 2. Single or Parallel Cable Run 3. Size of Cable	Hydel	CT4-TSHO
	Microlectric®	JS4B-INTLHO
	Eaton	TCC5-IN-H1
	Durham[2]	1011897-OH
CM Service Overhead/Underground	Durham[2]	1012109 (Overhead/Underground)
	Hydel	CTS405PW-TSHO w/ MSPMK7
	Eaton	TSU5C-H1C
	Microlectric®	CT105-SWLHO

[2]Contact Jesstec Industries Inc to order

[3]Main Service Box required ahead of the 400A main Multi-Position MMD as per Hydro One Retail Metering Guide Figure 2C

Three Phase, Four-Wire Service, Self-Contained

120/208 to 347/600V 7-Jaw ANSI Form Factor 16S

SERVICE & TYPE	REQUIREMENT
100A Overhead	Refer to "**Meter-Mounting Device (MMD) Requirements**" on Page 1.
200A Overhead/Underground	

Where the 16S MMD is required to be installed in a permanent outdoor enclosure, please see detail Figure 4 of the Hydro One Retail Metering Guide.

THE LIST OF THIRD PARTY-MANUFACTURED EQUIPMENT IS PROVIDED FOR YOUR CONVENIENCE ONLY AND DOES NOT IMPLY AN ENDORSEMENT, GUARANTEE, WARRANTY, OR RECOMMENDATION BY HYDRO ONE NETWORKS INC. OR ITS AFFILIATES (AND THEIR RESPECTIVE DIRECTORS, EMPLOYEES, PARTNERS, AND AGENTS) (COLLECTIVELY, "HYDRO ONE") AND HYDRO ONE MAKES NO REPRESENTATIONS OR WARRANTIES ABOUT ANY PRODUCTS OR SERVICES PROVIDED BY THE PARTIES WHOSE PRODUCES OR SERVICES ARE LISTED. HYDRO ONE IS NOT RESPONSIBILE FOR THE PERFORMANCE OF METER-MOUNTING DEVICES AND OTHER EQUIPMENT AND SERVICES PROVIDED BY THIRD PARTIES, INCLUDING, WITHOUT LIMITATION, ANY DEFECTS OR MALFUNCTIONS IN THE EQUIPMENT OR SERVICES THAT RESULTS IN (1) INCORRECT METER READINGS OF CONSUMPTION OF ELECTRICITY, (2) DAMAGES CAUSED TO PROPERTY BELONGING TO OWNER, HYDRO ONE, OR THIRD PARTY, OR (3) PERSONAL INJURY OR DEATH.