

Hydro One Networks Inc. 483 Bay Street Toronto, Ontario M5G 2P5

NEEDS ASSESSMENT REPORT

GTA North Region

Date: July 14, 2023

Prepared by: GTA North Region Technical Working Group











Disclaimer

This Needs Assessment Report was prepared for the purpose of identifying potential needs in the GTA North Region and to recommend which need: a) does not require further regional coordination and b) identify needs requiring further assessment and/or regional coordination. The results reported in this Needs Assessment are based on the input and information provided by the Technical Working Group ("TWG") for this region.

The TWG participants, their respective affiliated organizations, and Hydro One Networks Inc. (collectively, "the Authors") shall not, under any circumstances whatsoever, be liable to each other, to any third party for whom the Needs Assessment Report was prepared ("the Intended Third Parties") or to any other third party reading or receiving the Needs Assessment Report ("the Other Third Parties"). The Authors, Intended Third Parties and Other Third Parties acknowledge and agree that: (a) the Authors make no representations or warranties (express, implied, statutory or otherwise) as to this document or its contents, including, without limitation, the accuracy or completeness of the information therein; (b) the Authors, Intended Third Parties and Other Third Parties and their respective employees, directors and agents (the "Representatives") shall be responsible for their respective use of the document and any conclusions derived from its contents; (c) and the Authors will not be liable for any damages resulting from or in any way related to the reliance on, acceptance or use of the document or its contents by the Authors, Intended Third Parties or Other Third Parties or their respective Representatives.

Executive Summary

Region	GTA North Region (the "Region")						
Lead	Hydro One Networks Inc. ("Hydro One")						
Start Date	March 17, 2023 End Date July 14, 2023						
1. INTRODUCTION							

The second Regional Planning ("RP") cycle for the GTA North Region was completed in October 2020 with the publication of the Regional Infrastructure Plan ("RIP") report. This is the third RP cycle for this Region, which begins with the Needs Assessment ("NA") phase. The purpose of this NA is to:

- a) Identify any new needs and reaffirm needs identified in the previous RP cycle; and
- b) Recommend which needs:
 - i. require further assessment and regional coordination (and hence, proceed to the next phases of RP); and
 - ii. do not require further regional coordination (i.e., can be addressed directly between Hydro One and the impacted Local Distribution Companies ("LDC") to develop a preferred plan, or no regional investment is required at this time and the need may be reviewed during the next RP cycle.

2. **REGIONAL ISSUE/TRIGGER**

In accordance with the RP process, the RP cycle should be triggered at least once every five years. Considering these timelines, the third Regional Planning cycle was triggered in March 2023 for the GTA North Region.

3. SCOPE OF NEEDS ASSESSMENT

The scope of the GTA North Region NA includes:

- a) Reaffirm and update needs/plans identified in the previous RP cycle;
- b) Identify any new needs resulting from this assessment.
- c) Recommend which need(s) require further assessment and regional coordination in the next phases of the RP cycle; and
- d) Recommend which needs do not require further regional coordination (i.e., can be addressed directly between Hydro One and the impacted LDC(s) to develop a preferred plan, or no regional investment is required at this time and the need may be reviewed during the next RP cycle).

The Technical Working Group ("TWG") may also identify additional needs during the next phases of the planning process, namely Scoping Assessment ("SA"), Integrated Regional Resource Plan ("IRRP") and RIP, based on updated information available at that time.

The planning horizon for this NA is 10 years.

4. INPUTS/DATA

The TWG representatives from LDCs, the Independent Electricity System Operator ("IESO"), and Hydro One provided input and relevant information for the GTA North Region regarding capacity needs, system reliability needs, operational issues, and major high-voltage ("HV") transmission assets requiring replacement over the planning horizon.

The provincial push towards decarbonization as outlined in the IESO's "Pathways to Decarbonization" report published on December 15, 2022, is expected to impact the electricity demand over the longer term. As a result, the electricity demand, and the need for new infrastructure over the longer term could be higher than previously anticipated or as discussed in this report. The impact of decarbonization will be considered during the next phases of this regional planning cycle.

5. ASSESSMENT METHODOLOGY

The assessment's primary objective is to identify the electrical infrastructure needs in the Region over the study period. The assessment methodology includes a review of planning information such as load forecast, conservation, and demand management ("CDM") forecast, available distributed generation ("DG") information, system reliability and operation issues, and major HV transmission assets requiring replacement.

A technical assessment of needs was undertaken based on:

- a) Station capacity and transmission adequacy;
- b) System reliability and any operational concerns;
- c) Major HV transmission equipment requiring replacement with consideration to "right-sizing"; and
- d) Sensitivity analysis to capture uncertainty in the load forecast and variability of demand drivers such as electrification.

6. NEEDS

Needs that were identified in the last RP cycle with current need dates are as follows:

- New Markham MTS #5 need date is 2028
- Uprate 230kV circuits P45/46 from Parkway TS to Markham MTS #4 Jct. need date is 2028
- New Northern York TS need date is 2027
- Woodbridge TS: Replace transformer T5 with similar and size equipment as per current standard need date is 2027
- New Vaughan MTS #5 need date is 2030
- Claireville TS x Brown Hill TS Transmission circuit capacity need need date is 2030
- Load Restoration and/or Security needs for 230kV circuits V43/V44, H82V/H83V, and V71P/V75P Existing need¹

New needs identified in this NA are:

- Kleinburg TS 44kV: Load transfer to Northern York TS need date is 2027
- New Vaughan MTS #6 need date is 2027
- New Toubner TS (CTS) need date is 2027
- New Richmond Hill MTS #3 need date is 2032
- Load Restoration needs for 230kV circuits P45/P46 need date is 2027

7. **RECOMMENDATIONS**

The TWG's recommendations are as follows:

- a) No further regional coordination is required for the following need and work will be proceeding as planned:
 - Woodbridge TS: Replace transformer T5
 - Toubner TS: Build new station
 - Vaughan MTS #6: Build new station
- b) Further assessment and regional coordination is required in the next phases of the RP cycle to review and/or develop a preferred plan for the follow needs:
 - Kleinburg TS 44kV: Load transfer to Northern York TS
 - Markham MTS #5: Build new station
 - 230kV circuit P45/P46: Uprate circuits between Parkway TS and Markham MTS #4 Jct.
 - Northern York TS: Build new station
 - Vaughan MTS #5: Build new station
 - Richmond Hill MTS #3: Build new station
 - Claireville TS x Brown Hill TS Transmission circuit capacity need and load restoration needs
 - Load Restoration and/or Security needs for 230kV circuits V43/V44, H82V/H83V, P45/P46, and V71P/V75P

1. No action considered was considered necessary in the last regional planning cycle

TABLE OF CONTENTS

1	Introduc	tion	7
2	Regiona	l Issue/Trigger	7
3	Scope of	Needs Assessment	7
4	Regiona	l Description and Connection Configuration	8
5	Inputs an	nd Data	10
6	Assessm	ent Methodology	10
7	Adequad	y of Existing Facilities	
7.1	Adeo	quacy of Northern and Southern York Area Facilities	
	7.1.1	500 and 230 kV Transmission Facilities	
	7.1.2	Step down Transformer Station Facilities	
7.2	Asse	t Renewal Needs	14
7.3	Load	Restoration and Load Security Needs	14
8	Needs		16
8.1	Stati	on and Transmission Capacity Needs in the Near and Medium Term	
	8.1.1	Markham Area - Build Markham MTS #5 and Uprate circuits P45/P46 -2027	17
	8.1.2 B88H/B8	Northern York Region - Build Northern York Area TS and supply from 2 39H - 2027	
	8.1.3	Vaughan Area – Build Vaughan MTS #5 and supply from 230kV Line H82V/H 19	H83V -2030
	8.1.4	Kleinburg TS Area – Transfer Load to Northern York TS	20
	8.1.4 8.1.5	Kleinburg TS Area – Transfer Load to Northern York TS Vaughan Area – Build Vaughan MTS #6 and supply from 230kV Line V43/V4	
	8.1.5 8.1.6		4 - 2027.20 Line V71P /
	8.1.5 8.1.6	Vaughan Area – Build Vaughan MTS #6 and supply from 230kV Line V43/V4 Richmond Hill Area – Build Richmond Hill MTS #3 and supply from 230kV I	4 - 2027.20 Line V71P /
	8.1.5 8.1.6 V75P - 2	Vaughan Area – Build Vaughan MTS #6 and supply from 230kV Line V43/V4 Richmond Hill Area – Build Richmond Hill MTS #3 and supply from 230kV 1 032	4 - 2027.20 Line V71P / 21
8.2	8.1.5 8.1.6 V75P - 2 8.1.7 8.1.8	Vaughan Area – Build Vaughan MTS #6 and supply from 230kV Line V43/V4 Richmond Hill Area – Build Richmond Hill MTS #3 and supply from 230kV 1 032 Toubner TS - 2027	4 - 2027.20 Line V71P / 21 22
8.2 8.3	8.1.5 8.1.6 V75P - 2 8.1.7 8.1.8 Long	Vaughan Area – Build Vaughan MTS #6 and supply from 230kV Line V43/V4 Richmond Hill Area – Build Richmond Hill MTS #3 and supply from 230kV 1 032 Toubner TS - 2027 Claireville x Brown Hill Transmission capacity Need- 2030	4 - 2027.20 Line V71P / 21 22 22 22
	8.1.5 8.1.6 V75P - 2 8.1.7 8.1.8 Long Asse	Vaughan Area – Build Vaughan MTS #6 and supply from 230kV Line V43/V4 Richmond Hill Area – Build Richmond Hill MTS #3 and supply from 230kV 1 032 Toubner TS - 2027 Claireville x Brown Hill Transmission capacity Need- 2030 g-Term Capacity Needs	4 - 2027.20 Line V71P / 21 22 22 22 22
8.3	8.1.5 8.1.6 V75P - 2 8.1.7 8.1.8 Long Assee	Vaughan Area – Build Vaughan MTS #6 and supply from 230kV Line V43/V4 Richmond Hill Area – Build Richmond Hill MTS #3 and supply from 230kV 1 032 Toubner TS - 2027 Claireville x Brown Hill Transmission capacity Need- 2030 g-Term Capacity Needs t Renewal Needs for Major HV Transmission Equipment – Woodbridge TS	4 - 2027.20 Line V71P / 21 22 22 22 22 22 22
8.3 8.4	8.1.5 8.1.6 V75P - 2 8.1.7 8.1.8 Long Asse Load	Vaughan Area – Build Vaughan MTS #6 and supply from 230kV Line V43/V4 Richmond Hill Area – Build Richmond Hill MTS #3 and supply from 230kV 1 032 Toubner TS - 2027 Claireville x Brown Hill Transmission capacity Need- 2030 g-Term Capacity Needs t Renewal Needs for Major HV Transmission Equipment – Woodbridge TS Restoration and Security Needs	4 - 2027.20 Line V71P / 21 22 22 22 22 22 22 23
8.3 8.4 9	8.1.5 8.1.6 V75P - 2 8.1.7 8.1.8 Long Asse Load Sensitivi Recomm	Vaughan Area – Build Vaughan MTS #6 and supply from 230kV Line V43/V4 Richmond Hill Area – Build Richmond Hill MTS #3 and supply from 230kV 1 032 Toubner TS - 2027 Claireville x Brown Hill Transmission capacity Need- 2030 g-Term Capacity Needs t Renewal Needs for Major HV Transmission Equipment – Woodbridge TS I Restoration and Security Needs	4 - 2027.20 Line V71P / 21 22 22 22 22 22 23 23 24
 8.3 8.4 9 10 	8.1.5 8.1.6 V75P - 2 8.1.7 8.1.8 Long Asse Load Sensitivi Recomm	Vaughan Area – Build Vaughan MTS #6 and supply from 230kV Line V43/V4 Richmond Hill Area – Build Richmond Hill MTS #3 and supply from 230kV 1 032 Toubner TS - 2027 Claireville x Brown Hill Transmission capacity Need- 2030 g-Term Capacity Needs t Renewal Needs for Major HV Transmission Equipment – Woodbridge TS Restoration and Security Needs ty Analysis	4 - 2027.20 Line V71P / 21 22
 8.3 8.4 9 10 11 	8.1.5 8.1.6 V75P - 2 8.1.7 8.1.8 Long Asse Load Sensitivi Recomm Reference Appendi	Vaughan Area – Build Vaughan MTS #6 and supply from 230kV Line V43/V4 Richmond Hill Area – Build Richmond Hill MTS #3 and supply from 230kV 1 032 Toubner TS - 2027 Claireville x Brown Hill Transmission capacity Need- 2030 g-Term Capacity Needs t Renewal Needs for Major HV Transmission Equipment – Woodbridge TS Restoration and Security Needs ty Analysis hendations	4 - 2027.20 Line V71P / 21 22 22 22 22 22 22 23 23 24 24 25
 8.3 8.4 9 10 11 12 	8.1.5 8.1.6 V75P - 2 8.1.7 8.1.8 Long Asse Load Sensitivi Recomm Reference Appendi Appendi	Vaughan Area – Build Vaughan MTS #6 and supply from 230kV Line V43/V4 Richmond Hill Area – Build Richmond Hill MTS #3 and supply from 230kV 1 032 Toubner TS - 2027 Claireville x Brown Hill Transmission capacity Need- 2030 g-Term Capacity Needs t Renewal Needs for Major HV Transmission Equipment – Woodbridge TS l Restoration and Security Needs ty Analysis endations x A. Stations in the GTA North Region	4 - 2027.20 Line V71P / 21 22 22 22 22 23 23 23 24 24 24 25 26
 8.3 8.4 9 10 11 12 13 	8.1.5 8.1.6 V75P - 2 8.1.7 8.1.8 Long Asse Load Sensitivi Recomm Reference Appendi Appendi	Vaughan Area – Build Vaughan MTS #6 and supply from 230kV Line V43/V4 Richmond Hill Area – Build Richmond Hill MTS #3 and supply from 230kV 1 032 Toubner TS - 2027 Claireville x Brown Hill Transmission capacity Need- 2030 g-Term Capacity Needs t Renewal Needs for Major HV Transmission Equipment – Woodbridge TS l Restoration and Security Needs ty Analysis hendations ess x A. Stations in the GTA North Region x B. Transmission Lines in the GTA North Region	4 - 2027.20 Line V71P / 21 22 22 22 22 23 23 24 24 24 24 25 26 26

List of Tables and Figures

Table 1-1: GTA North Region TWG Participants 7
Figure 4-1: GTA North Region Map
Figure 4-2: GTA North Region– Single Line Diagram
Table 7-1 Loading on Claireville TS x Brown Hill TS Corridor
Table 7-2 Loading on the Parkway TS x Markham MTS #4 Jct. Section of 230kV Line P45/P4613
Table 7-3 Step-Down Transformer Stations in the GTA North Region 13
Table 8-1 Near and Medium Terms Needs in the GTA North Region 16
Figure 8-1: Markham MTS #5 Location17
Figure-8-2 Northern York Area TS – Potential Location
Table 8-2: Northern York Area Capacity Need 18
Figure-8-3 Vaughan MTS #5 Location
Table 8-3: Vaughan Area Station Capacity Need 19
Table 8-4 Kleinburg Area Station Capacity Load
Figure-8-4 Vaughan MTS #6 Location
Table 8-5: Loading on the 230kV Claireville TS x Kleinburg TS line V43/V4421
Figure-8-5 Richmond Hill MTS #3 Location
Table 9-1: Impact of Sensitivity Analysis on the Identified Capacity Needs 23

1 INTRODUCTION

The second cycle of the Regional Planning ("RP") process for the GTA North Region was completed in October 2020 with the publication of the Regional Infrastructure Plan ("RIP") report.

This is the third RP cycle for this Region, which begins with the Needs Assessment ("NA") phase. The purpose of this Needs Assessment ("NA") is to identify new needs in the region, reaffirm and update previously identified needs in the last GTA North RP cycle, and recommend which needs require further assessment and regional coordination.

This report was prepared by the GTA North Region Technical Working Group ("TWG"), led by Hydro One Networks Inc. Participants of the TWG are listed below in Table 1. The report presents the results of the assessment based on information provided by Hydro One, the Local Distribution Companies ("LDCs") and the Independent Electricity System Operator ("IESO").

Company
Alectra Utilities Corporation
Hydro One Networks Inc. (Distribution)
Independent Electricity System Operator ("IESO")
Newmarket-Tay Power Distribution Ltd
Toronto Hydro-Electric System Limited ("THESL")
Hydro One Networks Inc. (Lead Transmitter)

2 **REGIONAL ISSUE/TRIGGER**

In accordance with the RP process, the RP cycle should be triggered at least once every five years. Considering these timelines, the third RP cycle was triggered for the GTA North Region.

3 SCOPE OF NEEDS ASSESSMENT

The scope of this NA covers the GTA North Region and includes:

- Reaffirm and update needs/plans identified in the previous RP cycle.
- Identify any new needs resulting from this assessment.
- Recommend which need(s) require further assessment and regional coordination in the next phases of the RP cycle; and
- Recommend which need(s) that do not require further regional coordination (i.e., can be addressed directly between Hydro One and the impacted LDC(s) to develop a preferred plan, or no regional investment is required at this time and the need may be reviewed during the next RP cycle).

The TWG may identify additional needs during the next phases of the RP process, namely Scoping Assessment ("SA"), Integrated Regional Resource Plan ("IRRP"), and/or RIP based on updated information available at that time.

4 REGIONAL DESCRIPTION AND CONNECTION CONFIGURATION

The GTA North Region is comprised of the Northern York Area, Southern York Area, and the Western Area. Electrical supply to the region is provided from sixteen 230kV step-down transformer stations. The 2022 Summer Peak area load of the region was approximately 2249MW. Please refer to Figure 4-1.




Figure 4-1: GTA North Region Map

Electrical supply to the GTA North Region is primarily provided from three major 500/230 kV autotransformer stations, namely Claireville TS, Parkway TS, and Cherrywood TS, and a 230 kV transmission network supplying the various step-down transformation stations in the region. Local generation in the Region consists of the 393 MW York Energy Centre connected to the 230 kV circuits B88H/B89H in King Township. Please refer to Figure 4-2.

The Northern York Area encompasses the municipalities of Aurora, Newmarket, King, East Gwillimbury, Whitchurch-Stouffville and Georgina, as well as some load in Simcoe County that is supplied from the same electricity infrastructure. It is supplied by Claireville TS, a 500/230 kV autotransformer station, and

three 230 kV transformer stations stepping down the voltage to 44 kV. The York Energy Centre provides a local supply source in Northern York Area. The LDCs supplied in the Northern York Area are Hydro One Distribution, Newmarket-Tay Power Distribution, and Alectra.

The Southern York Area includes the municipalities of Vaughan, Markham, and Richmond Hill. It is supplied by three 500/230 kV autotransformer stations (Claireville TS, Parkway TS, and Cherrywood TS), nine 230 kV transformer stations (includes eight LDC owned stations and one Hydro One owned) stepping down the voltage to 27.6 kV, and one other direct transmission connected load customer. The LDC supplied in the Southern York Area is Alectra.

The Western Area comprises the Western portion of the municipality of Vaughan. Electrical supply to the area is provided through Claireville TS, a 500/230 kV autotransformer station, and a 230 kV tap (namely, the "Kleinburg tap") that supplies three 230 kV transformer stations (including one LDC owned transformer station) stepping down the voltage to 44 kV and 27.6 kV. The LDCs directly supplied are Alectra and Hydro One Distribution. Embedded LDCs include Alectra and Toronto Hydro.




Figure 4-2: GTA North Region-Single Line Diagram

The transformer stations and circuits in the area are listed in Appendix A and Appendix B.

5 INPUTS AND DATA

TWG participants, including representatives from LDCs, IESO, and Hydro One provided information and input for the GTA North Region NA. The information provided includes the following:

- Load Forecast for all supply stations in the GTA North Region.
- Known capacity and system reliability needs, operational issues, and/or major HV transmission equipment requiring replacement over the study period; and
- Planned/foreseen transmission and distribution investments that are relevant to the GTA North RP process.

In December 2022, the IESO published a report¹ on developing an achievable pathway to the decarbonization of the electricity system. As a result, the electricity demand, and the need for new infrastructure over the longer term could be higher than anticipated or discussed in this report. The impact of the decarbonization and resulting electrification will be considered during the next phase of this regional planning cycle.

6 ASSESSMENT METHODOLOGY

The following methodology and assumptions are made in this Needs Assessment:

- Load forecast: The LDCs provided their load forecast for all the stations supplying their loads in the GTA North Region for the 10-year study period. The IESO provided a Conservation and Demand Management ("CDM") forecast and Distributed Generation ("DG") contract information for the Toronto Region. The region's extreme summer non-coincident peak gross load forecast for each station was prepared by applying the growth rates from the LDC load forecast to the actual 2022 summer peak extreme weather corrected loads. The extreme summer weather correction factor was provided by Hydro One. The net extreme weather summer load forecast was produced by reducing the gross load forecast for each station by the percentage CDM from the IESO for that station. The extreme summer weather corrected net non-coincident peak for the individual stations in the GTA North Region are given in Appendix C.
- Relevant information regarding system reliability and operational issues in the region;
- List of major HV transmission equipment planned and/or identified to be replaced based on asset condition assessment, and relevant for RP purposes. The scope of equipment considered is given in Section 7.1.

A technical assessment of needs was undertaken based on:

- Station capacity and transmission adequacy assessment.
- System reliability and operational considerations.

¹ IESO Report, "Pathways-to-Decarbonization", Dec15, 2022

- Asset renewal for major HV transmission equipment requiring replacement with consideration to "right-sizing"; and
- Sensitivity analysis to capture uncertainty in the load forecast

The following other assumptions are made in this report.

- The study period for this NA is 2023-2032.
- Coincident loads have been assumed equal to non-coincident loads for the purpose of transmission line adequacy assessment.
- Station capacity adequacy is assessed by comparing the non-coincident peak load with the station's normal planning supply capacity, assuming a 90% lagging power factor for stations having no low-voltage (LV) capacitor banks and 95% lagging power factor for stations having LV capacitor banks.
- Normal planning supply capacity for transformer stations is determined by the Hydro One summer 10-Day Limited Time Rating (LTR) of a single transformer at that station.
- Adequacy assessment is conducted as per Ontario Resource Transmission Assessment Criteria (ORTAC).

7 ADEQUACY OF EXISTING FACILITIES

This section provides a review of the adequacy of the transmission lines and stations in the GTA North Region. The adequacy is assessed using the latest extreme weather peak summer regional load forecast provided in Appendix C.

7.1 Adequacy of Northern and Southern York Area Facilities

7.1.1 500 and 230 kV Transmission Facilities

All 500 and most 230 kV transmission circuits in the GTA North are classified as part of the Bulk Electricity System ("BES"). The 230 kV circuits also serve local area stations within the region. The Northern and Southern York Areas are comprised of the following 230 kV circuits. Refer to Figure 4-2.

Northern York Area:

- Claireville TS to Holland TS 230 kV circuits: H82V and H83V.
- Holland TS to Brown Hill TS 230 kV circuits: B88H and B89H.

Southern York Area:

- Parkway TS to Cherrywood TS 230 kV circuits: C35P and C36P.
- Parkway TS to Claireville TS 230 kV circuits: V71P and V75P.
- Parkway TS to Buttonville TS ("Buttonville Tap") 230 kV circuits: P45 and P46².
- Parkway TS to Richview TS 230 kV circuits: P21R and P22R.

Western Area:

• Claireville TS to Kleinburg TS 230 kV circuits: V43 and V44³

The NA review shows that all flows on all transmission lines are within rating during the 2023-2032 study period except for the Claireville x Brown Hill corridor and the Parkway TS to Buttonville TS line. These are discussed below:

1) Loading on the Claireville TS to Brown Hill TS 230kV Corridor comprising the double circuit line H82/H3V and B88H/B89H will exceed the thermal limits by summer 2030.

² Radial from Parkway TS

³ Radial from Claireville TS

Transformer Station	Limi t MW	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	Nee d Date
Armitage TS (44kV)		285	290	296	301	305	303	305	308	311	313	
Brown Hill TS (44kV)		94	100	118	121	125	124	125	125	126	126	
Holland TS (44kV)		166	173	176	179	169	169	169	169	169	169	
Northern York Station						66	80	89	99	109	118	
Vaughan MTS #4 (28kV)		101	100	128	149	148	147	146	145	143	142	
Vaughan MTS #5 (28kV)									64	132	138	
Total	850	646	663	718	750	813	823	834	911	989	1007	2030

Table 7-1 Loading on Claireville TS x Brown Hill TS Corridor

2) Loading on the Parkway TS x Markham MTS #4 Jct. section of the 230kV Parkway TS x Buttonville TS double circuit Line P45/P46 will exceed the rating of line by summer 2028

Transformer Station	Limit MW	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	Need Date
Buttonville TS (28kV)		144	152	154	152	160	149	148	147	146	145	
Markham MTS #4(28kV)		116	117	141	162	191	177	175	174	173	171	
Markham MTS #5(28kV)							68	136	140	139	138	
Toubner TS (28kV)						32	31	50	52	55	72	
Total	420	260	269	294	314	384	425	509	513	513	526	2028

 Table 7-2 Loading on the Parkway TS x Markham MTS #4 Jct. Section of 230kV Line P45/P46

7.1.2 Step down Transformer Station Facilities

There are a total of fifteen Hydro One and LDC owned step-down transformers stations and one direct transmission connected industrial customer owned station in the GTA North Region as given in Table 7-3 Step-Down Transformer Stations in the GTA North Region below:

Table 7-3 Step-Down	Transformer	Stations in the	GTA North Region
Table 7-5 Step-Down	1 1 1 ansi 01 mei	Stations in the	OTA North Region

Northern York Area								
Armitage TS	Brown Hill TS	Holland TS						
Southern York Area								
Buttonville TS	Markham MTS #11	Markham MTS #21						
Markham MTS #31	Markham MTS #41	Richmond Hill MTS ¹						
Vaughan MTS #11	Vaughan MTS #21	Vaughan MTS #41						
Industrial Customer								
Western Area								
Kleinburg TS	Vaughan MTS #31	Woodbridge TS						

1. Stations owned by Alectra

The loadings on these stations were reviewed. Based on the forecast in Appendix C, additional capacity is required in the Northern York, Markham, and Vaughan areas starting in 2027. The station loading in each area and the associated station capacity and need dates are summarized in Table 7-.

Area/Supply	LTR-Capacity (MW)	2023 Summer Forecast (MW)	Need Date
Northern York Area (Armitage TS, Holland TS)	485	452	2027
Northern York Area (Brown Hill)	184	94	-
Markham / Richmond Hill transformation Capacity (Buttonville TS, Markham MTS #1, 2, 3, 4, and Richmond Hill MTS #1, 2) ¹	957	847	2028
Vaughan Transformation Capacity (Vaughan MTS #1, 2, 4)	612	551	2030
Vaughan Transformation Capacity (Vaughan MTS #3) ²	153	145	2027
Kleinburg Area (Kleinburg TS 44kV)	97	102	Note ³
Woodbridge TS (44kV)	80	85	Note ⁴

1. Two stations required Markham MTS #5 in 2028 and Richmond Hill MTS #3 in 2032

2. Vaughan MTS #6 is a station dedicated for a large customer.

3. Excess load to be transferred to Northern York TS when new station complete in 2027

4. Loads to be managed by Hydro One Distribution

7.2 Asset Renewal Needs

No asset renewal needs have been identified in the GTA North Region over the current study period other than replacement of transformer T5 at Woodbridge TS listed in the 2020 RIP.

7.3 Load Restoration and Load Security Needs

Load Restoration and /or security needs were identified for theV43/V44, H82V/H83V, and V71P/V75P circuits in the 2020 RIP. One new load restoration need has been identified for the P45/P46 circuits. The needs and the recommended plan to address them are summarized below:

1. Load restoration following loss of the Claireville TS x Kleinburg TS 230kV circuits (V43/V44).

Not all loads more than 250 MW and 150 MW can be restored within 30 minutes and 4 hours respectively, as per the ORTAC restoration criteria. The RIP recommended that this need would be addressed as part of the longer-term plan to reinforce the Claireville TS to Kleinburg TS corridor. No further action was proposed at the time. This will be re-visited in the next phase of this RP cycle.

2. Load Restoration following loss of the Claireville TS to Holland TS circuits (H82V/H83V).

All loads exceeding 250 MW cannot be restored within 30 minutes per the ORTAC criteria. Following the loss of H82V/H83V, the normal station service supply to YEC generation is also lost. Holland TS cannot be restored from B88H/B89H until YEC generation is restored. Transferring YEC to an alternate source of station service supply cannot be completed within 30 minutes. The RIP had recommended that the IESO pursue alternative station service configurations at YEC to facilitate faster restoration of load on H82V/H83V, consistent with the load restoration criteria. This will be re-visited in the next phase of this regional planning cycle.

3. Load Security Need for the Parkway TS to Claireville TS 230kV double circuit Line V71P/V75P

The loss of this line can result in an interruption to over the 600MW which is more than what is permitted under the ORTAC criteria. The RIP had recommended that no further action is required. While the load security criteria was not met, Hydro One has installed inline switches at Grainger Jct. – located just outside of Vaughan MTS #1 - which permits quick restoration of the loads. This will be re-visited in the next phase of this regional planning cycle.

4. Load Restoration Need for the Parkway TS to Buttonville TS 230kV double circuit Line P45/P46

The line loading is expected to reach 384MW by summer 2027. Not all loads more than 250 MW and 150 MW can be restored within 30 minutes and 4 hours respectively for a double circuit outage, as per the ORTAC restoration criteria. This is a new need and will be reviewed in the next phase of this regional planning cycle.

8 NEEDS

This section identifies any new needs in the GTA North Region and reaffirms and provides an update on the needs already identified in the previous RIP.

No.	Need	Need Date ¹	
Need	s as per last RIP ²		
1	Northern York Area: Step-down Transformation Capacity	Build new Northern York Station	2027
2	Woodbridge TS: End-of-life of transformer T5	Replace the end-of-life transformer with similar type and size equipment as per current standard	2027
3	Markham Area: Step-down Transformation Capacity	Build new Markham #5 MTS and connect to 230kV circuits P45/P46	2028
4	Increase Capability of 230kV Circuits P45+P46 (supply Buttonville TS, Markham #4 MTS, and future Markham #5 MTS)	Uprate circuits P45/46 from Parkway to Markham MTS #4 Jct.	2028
5	Vaughan Area: Step-down Transformation Capacity	Build new Vaughan MTS #5	2030
6	Claireville X Brownhill Circuit Upgrade	Uprate circuits- H82/H3V and B88H/B89H	2030
7	Load Restoration and/or Security needs for 230kV circuits V43/V44, H82V/H83V, and V71P/V75P ³	To be reviewed in next phase of this regional planning cycle	Existing
New	Needs identified		
8	Kleinburg TS Area	Transfer load to Northern York TS	2027
9	Vaughan Area: Step-down Transformation Capacity	Build new Vaughan MTS #6 and connect to 230kV circuit V43/V44	2027
10	Markham Area: New Customer Connection	Build New Toubner TS and line tap to 230kV circuits P45/46	2027
11	Richmond Hill Area: Step-down Transformation Capacity	Build new Richmond Hill #3 MTS	2032
12	Load Restoration for 230kV circuits P45/46	To be reviewed in next phase of this regional planning cycle	2027

Table 8-1 Nea	r and Medium	n Terms Needs	in the GTA	North Region

1. Need date based on current forecast

2. Please see Reference 1 in Section 11

3. No action was considered necessary for these needs in the last regional Planning cycle. Needs will be reviewed again in the IRRP and RIP phases of this regional planning cycle.

8.1 Station and Transmission Capacity Needs in the Near and Medium Term

As shown in the Table above, the 2020 RIP had identified three new station capacity needs, one in the Markham area designated as Markham MTS #5, the second in the Vaughan Area, designated as Vaughan MTS #5 and the third in the Northern York Area, designated as Northern York TS. Since then, based on

the current load forecast and customers' request, the need for three additional stations has been identified over the study period - Richmond Hill MTS #3, Vaughan MTS #6 and Toubner TS.

8.1.1 Markham Area - Build Markham MTS #5 and Uprate circuits P45/P46 -2028

Markham MTS #5 was previously identified to provide additional step-down transformation capacity in Markham-Richmond Hill area and planned to be built adjacent to the Buttonville TS and supplied from the same 230kV Parkway TS x Buttonville TS circuits P45/P46 (See Figure 8-1 below). The new station will have 2 x75/125MVA, 230/27.6kV transformers and a 27.6kV switchgear building.




Figure 8-1: Markham MTS #5 Location

The TWG reaffirmed the need to build the new Markham MTS #5 and to uprate the limiting section of the P45/P46 line between Parkway TS and Markham MTS #4 Jct. to provide the needed capacity. The station project need date based on current forecast is summer 2028 (See Table 7-4) and the lines project need date is summer 2028 (see Table 7-2). This will be re-visited in the next phase of this regional planning cycle.

8.1.2 Northern York Region - Build Northern York Area TS and supply from 230kV Line B88H/B89H - 2027

The Northern York Area TS was recommended to be built in the Northern York Region to provide additional step-down transformation capacity in the Bradford, East Gwillimbury, and Newmarket area. This area is currently supplied from Armitage TS and Holland TS and total area load is forecast to exceed the capacity of these existing two stations by summer 2027 as shown in Table 8-2 below.





Transformer Station	LTR	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032
Armitage TS (44kV)	317	285	290	296	301	305	303	305	308	311	313
Holland TS (44kV) ¹	169	166	173	176	179	169	169	169	169	169	169
Northern York Station	170					66	80	89	99	109	118
Total	485	451	463	472	480	540	552	564	577	589	600

 Table 8-2: Northern York Area Capacity Need

1. Holland load above LTR to be transferred to new Northern York station.

The TWG has reaffirmed the need for building a new station close to these two stations, in the area shown in Figure 8-2. The new station is planned to be supplied from 230kV double circuit line H82V/H83V or B88H/B89H and planned to have 2x75/125MVA, 230/44-27.6kV transformers and 27.6kVand 44kV switchyards. The new station should increase the transformation capacity in Northern York Region by about 170 MW. The station location and timing will be further discussed with the area LDCs in the next phase of the regional planning process.

8.1.3 Vaughan Area – Build Vaughan MTS #5 and supply from 230kV Line H82V/H83V -2030

The Vaughan MTS #5 was previously identified to provide additional step-down transformation capacity in Vaughan area and planned to be built adjacent to the existing Vaughan MTS #4 – see Figure 8-3. The new station is planned to have 2 x75/125MVA, 230/27.6kV transformers, a 27.6kV switchgear building and is planned to be supplied from the 230kV double circuit line H82V/H83V.




Figure-8-3 Vaughan MTS #5 Location

Table 8-3: Vaughan Area Station	Capacity Need
---------------------------------	---------------

Transformer Station	LTR	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032
Vaughan MTS #1 (28kV)	306	301	297	294	291	288	286	283	281	279	277
Vaughan MTS #2 (28kV)	153	149	148	147	145	144	143	141	141	139	138
Vaughan MTS #4 (28kV)	153	101	100	128	149	148	147	146	145	143	142
Vaughan MTS #5 (28kV)									64	132	138
Total	612	551	545	569	585	580	575	570	631	694	696

As mentioned in Table 7-1, there isn't sufficient transmission capacity available on the Claireville to Brown Hill corridor to fully supply Vaughan MTS #5, given that a new station in Northern York is anticipated by 2027. Therefore, a plan to increase transmission supply capability to the area will be required before a plan for the new transformation station in Vaughan can be committed. This will be addressed in the next phase of this regional planning cycle.

8.1.4 Kleinburg TS Area – Transfer Load to Northern York TS

Kleinburg TS 44kV loading is a newly identified need. Kleinburg TS has 2 x 75/125MVA, 230/44-27.6kV transformers with separate 44kV and 27.6kV switchyards. Significant new load is forecast to connect at 44kV in the 2023-2024 period as shown in Table 8-4 below.

Transformer Station	Limit MW	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032
Kleinburg TS (28kV)	91	62	65	81	92	95	95	95	95	95	95
Kleinburg TS (44kV)	97	102	111	124	134	98	98	97	96	95	95
Load Transfer to be Managed		5	14	27	37						

Table 8-4 Kleinburg Area Station Capacity Load

To manage loading at Kleinburg TS, Hydro One DX intends to transfer loads in the northern area served by Kleinburg TS to the new Northern York TS planned to be in-service by 2027. The new Northern York TS is planned to be a 230/44-27.6kV station. The TWG will review this in the next phase of the regional planning cycle.

8.1.5 Vaughan Area – Build Vaughan MTS #6 and supply from 230kV Line V43/V44 - 2027

Vaughan MTS #6 is a new identified need. Alectra plans to build a new station to provide dedicated supply to a large customer. The new station will have 2 x 75/125MVA, 230/27.6kV transformers and a 27.6kV switchgear building. Alectra has requested that Hydro One build a short underground line tap to supply the new station from the 230kV Claireville TS x Kleinburg TS double circuit line V43/V44. The planned inservice date for the station is the end of 2027.




Figure-8-4 Vaughan MTS #6 Location

Transformer Station	Limit MW	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032
Kleinburg TS (28kV)		62	65	81	92	95	95	95	95	95	95
Kleinburg TS (44kV)		102	111	124	134	98	98	97	96	95	95
Vaughan MTS #3 (28kV)		117	118	118	145	145	145	145	145	145	145
Vaughan MTS #6 (28kV)						32	31	50	52	68	72
Woodbridge TS (28kV)		87	86	79	79	78	78	77	77	76	77
Woodbridge TS (44kV)		85	85	86	86	86	87	87	88	90	91
Total	620	453	465	487	536	534	533	552	553	569	575

 Table 8-5: Loading on the 230kV Claireville TS x Kleinburg TS line V43/V44

Table 8-5 shows the forecast loads connected to the line. As shown, there is adequate capacity to supply the loads over the study period.

Hydro One is currently in initial consultations with Alectra on the connection. Further details will be discussed in the next phase of the regional planning cycle.

8.1.6 Richmond Hill Area – Build Richmond Hill MTS #3 and supply from 230kV Line V71P / V75P - 2032

Richmond Hill MTS #3 is a new identified need. Alectra plans to build a new station to meet forecast loads in the 2030s. The new station will have 2 x 75/125MVA, 230/27.6kV transformers and a 27.6kV switchyard. Alectra has requested Hydro One to connect the new station to the 230kV Claireville TS x Parkway TS double circuit line V71P/V75P. The planned in-service date is summer 2032.




Figure-8-5 Richmond Hill MTS #3 Location

The 2020 RIP report had previously identified load security concerns with the V71P/V75P line as the connected loads exceed the 600 MW limit as per the ORTAC security criteria. However, as discussed in

Section 7.3, no action was recommended as Hydro One had installed sectionalizing switching on the line to restore load quickly in the event of a double circuit outage. The connection of the new station will further increase loading on the line. Alternatives to connect the station and address the load security need on the circuits will be developed and considered in the next phase of this RP cycle.

8.1.7 Toubner TS - 2027

Toubner TS is a new identified need. Hydro One has been requested to build a dedicated step-down transformer station for a direct industrial customer. The station will have 2 x 75/125 MVA, 230/27.6 kV transformers and a 27.6kV switchyard. The new station is in the Hwy. 7 and Hwy. 404 area and will be supplied from a tap for the 230kV line P45/P46 line tapped just north of Parkway TS. There is adequate capacity to supply the new station over the study period. The planned in-service date for the project is 2027.

Hydro One is currently in consultations with the customer to prepare connection estimates for the customer. Further details may be discussed in the current regional planning cycle.

8.1.8 Claireville x Brown Hill Transmission capacity Need- 2030

As described in Section 6.1 loading on the Claireville TS x Brown Hill TS corridor will exceed supply capacity by 2030. Alternatives to address this need will be developed and considered in the next phase of this regional planning cycle.

8.2 Long-Term Capacity Needs

With the provincial focus on decarbonization and the move away from fossil fuels, there will be a greater reliance on electricity. The GTA North region along with the rest of the province is about to embark on period of growth over the longer term driven by electrification, and large-scale development and customer connection projects are expected in several areas within the GTA North Region. The TWG will work with other stakeholders to ensure that all regional needs are met in a timely manner.

8.3 Asset Renewal Needs for Major HV Transmission Equipment – Woodbridge TS

As mentioned in Section 7.2 no asset renewal needs have been identified in the GTA North Region over the current study period other than Woodbridge TS identified in the last RIP.

Woodbridge TS comprises one DESN unit, T3/T5 (75/125 MVA), with two secondary winding voltages at 44 kV and 27.6 kV, each with a summer 10-Day LTR of 80 MW, supplying both Alectra and THESL. The station's 2022 44KV and 27.6kV actual peak loads were 55MW and 78 MW, respectively. Transformer T5 is currently about 51 years old and has been identified to be at its EOL.

The TWG is confirming the previous RIP identified need for the replacement of Woodbridge TS T5 transformer with similar type and size equipment as per current standard. Under this alternative the existing transformer T5 at Woodbridge TS is replaced with a new 75/125 MVA 230/44-27.6 kV transformer. This alternative would address the need and would maintain reliable supply to the customers in the area. The planned in-service date for the work is 2027.

8.4 Load Restoration and Security Needs

Load restoration need have been discussed earlier in Section 7.3, The TWG will consider these needs in the development of new plans to meet load growth and improve reliability of supply in the GTA North Region in the next phase of this regional planning cycle.

9 SENSITIVITY ANALYSIS

The objective of a sensitivity analysis is to capture uncertainty in the load forecast as well as variability of electric demand drivers to identify any emerging needs and/or advancement or deferment of recommended investments.

The uncertainty can stem from varying factors ranging from changes considered in potential evolution of public policy, electrification (e.g., electrification of transportation or other sectors), Municipal Energy Plans, Community Energy Plans, and Climate Action Plans (for actions that are not firm/committed), non-committed customer connections (both distribution and transmission), DER scenarios (e.g., battery storage), continued operation of off-contract generation.

A high demand growth forecast was developed by assuming that the forecast growth was 50% higher than the extreme summer corrected normal growth net load forecast given in Appendix C. Similarly, a low demand forecast was developed assuming that the growth was half the extreme summer corrected Normal Growth net load forecast.

The impact of sensitivity analysis for the high and low growth scenarios on the capacity needs identified in Table 8-1 is summarized in Table 9-1.

No.	Need	Normal Growth Scenario	High Growth Scenario	Low Growth Scenario
1	Toubner TS ¹	2027		
2	Vaughan MTS #6 ¹	2027		
3	Northern York TS	2027	2026	2027
4	Markham MTS #5	2028	2027	2032
5	Vaughan MTS #5	2030	2030	2031
6	Richmond Hill MTS #3	2032	2029	Beyond 2032
7	Uprate circuits P45/P46 ²	2028	2028	Beyond 2032
8	Claireville X Brown Hill Corridor	2030	2027	Beyond 2032

Table 9-1: Impact of Sensitivit	v Analysis on the Identified	Capacity Needs
1		1 2

¹Customer requested work with defined in-service date. ²To be done along with the Markham MTS #5 project

Based on current equipment deliverability and construction schedules the earliest in-service dates for projects is summer 2027. The Toubner TS, Vaughan MTS #6 are customer driven projects and need to proceed. The remaining needs listed in Table 9-1will be addressed in the next phases of this planning cycle

in coordination with the additional identified network capacity and load security/restoration needs and considering a longer-term forecast for the area.

10 RECOMMENDATIONS

The TWG's recommendations are as follows:

- a) No further regional coordination is required for the following needs and work will be proceeding as planned with all the three projects expected to be in-service by 2027.
 - Woodbridge TS: Replace transformer T5
 - Toubner TS: Build new station.
 - Vaughan MTS #6: Build new station
- b) Further assessment and regional coordination is required in the next phases of the regional planning cycle to review and/or develop a preferred plan for the follow needs:
 - Markham MTS #5: Build new station
 - 230kV circuit P45/P46: Uprate circuits between Parkway TS and Markham MTS #4 Jct.
 - Northern York TS: Build new station
 - Kleinburg TS 44kV: 44kV loads transfer to Northern York TS
 - Vaughan MTS #5: Build new station
 - Richmond Hill MTS #3: Build new station
 - Claireville TS x Brown Hill TS Transmission circuit capacity need
 - Load Restoration and/or Security needs for 230kV circuits V43/V44, H82V/H83V, P45/P46, and V71P/V75P.

11 References

- [1]. Hydro One, "GTA North Regional Infrastructure Plan", October 22, 2020. GTA North REGIONAL INFRASTRUCTURE PLAN (hydroone.com)
- [2]. Hydro One, "Need Assessment Report, GTA North Region", March 18, 2018. Needs Assessment Report GTA North Region (hydroone.com)
- [3]. IESO, "York Region: Integrated Regional Resource Plan", February 28, 2020. <u>York IRRP-20200228.pdf</u>
- [4]. IESO, "York Region Scoping Assessment Outcome Report", August 28, 2018. <u>York-Region-Scoping Assessment-Outcome-Report-20180828.pdf</u>

12 APPENDIX A. STATIONS IN THE GTA NORTH REGION

No.	Station (DESN)	Voltage (kV)	Supply Circuits
1	Armitage TS T1/T2	230/44	B88H/B89H
	Armitage TS T3/T4	230/44	B88H/B89H
2	Brown Hill TS T1/T2	230/44	B88H/B89H
3	Buttonville TS T3/T4	230/27.6	P45/P46
4	CTS	230/13.8	P21R/P22R
5	Holland TS T1/T2, T3/T4	230/44	H82V/H83V
6	Kleinburg TS T1/T2 27.6	230/27.6	V44/V43
	Kleinburg TS T1/T2 44	230/44	V44/V43
7	Markham MTS #1 T1/T2	230/27.6	P21R/P22R
8	Markham MTS #2 T1/T2	230/27.6	C35P/C36P
9	Markham MTS #3 T1/T2	230/27.6	C35P/C36P
	Markham MTS #3 T3/T4	230/27.6	C35P/C36P
10	Markham MTS #4 T1/T2	230/27.6	P45/P46
11	Richmond Hill MTS #1 T1/T2	230/27.6	V71P/V75P
	Richmond Hill MTS #2 T3/T4	230/27.6	V71P/V75P
12	Vaughan MTS #1 T1/T2	230/27.6	V71P/V75P
	Vaughan MTS #1 T3/T4	230/27.6	V71P/V75P
13	Vaughan MTS #2 T1/T2	230/27.6	V71P/V75P
14	Vaughan MTS #3 T1/T2	230/27.6	V44/V43
15	Vaughan MTS #4 T1/T2	230/27.6	H82V/H83V
16	Woodbridge TS T3/T5 27.6	230/27.6	V44/V43
	Woodbridge TS T3/T5 44	230/44	V44/V43

13 APPENDIX B. TRANSMISSION LINES IN THE GTA NORTH REGION

Line	Circuit Designations	Voltage (kV)
Claireville TS to Holland TS	H82V/H83V	230
Holland TS to Brown Hill TS	B88H / B89H	230
Claireville TS to Kleinburg TS	V43/V44	230
Claireville TS to Parkway TS	V71P/V75P	230
Parkway TS to Markham MTS #1 and CTS	P21R/P22R	230
Parkway TS to Buttonville TS	P45/P46	230
Parkway TS to Cherrywood TS	C35P/C36P	230

14 APPENDIX C: NON-COINCIDENT SUMMER PEAK NET LOAD FORECAST (2023 TO 2032)

	LTR	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032
Armitage TS (44kV)	317	285	290	296	301	305	303	305	308	311	313
Brown Hill TS (44kV)	184	94	100	118	121	125	124	125	125	126	126
Buttonville TS (28kV)	166	144	152	154	152	160	149	148	147	146	145
Holland TS (44kV)	169	166	173	176	179	169	169	169	169	169	169
Kleinburg TS (28kV)	91	62	65	81	92	95	95	95	95	95	95
Kleinburg TS (44kV) ¹	97	102	111	124	134	98	98	97	96	95	95
Markham MTS #1 (28kV)	81	80	79	78	77	76	76	75	74	74	73
Markham MTS #2 (28kV)	101	88	98	97	96	106	94	93	93	92	91
Markham MTS #3 (28kV)	202	171	184	191	189	197	186	184	183	181	180
Markham MTS #4(28kV)	153	116	117	141	162	176	177	175	174	173	171
Markham MTS #5(28kV)	153						68	136	140	139	138
Northern York Station	170					66	80	89	99	109	118
Richmond Hill-1 MTS (28kV)	153	153	152	150	149	154	146	144	144	142	141
Richmond Hill-2 MTS (28kV)	101	95	105	104	104	111	104	104	104	105	105
Richmond Hill-3 MTS (28kV)	153										60
Toubner TS (28kV)	153					32	31	50	52	55	72
Vaughan MTS #1 (28kV)	306	301	297	294	291	288	286	283	281	279	277
Vaughan MTS #2 (28kV)	153	149	148	147	145	144	143	141	141	139	138
Vaughan MTS #3 (28kV)	153	117	118	118	145	145	145	145	145	145	145
Vaughan MTS #4 (28kV)	153	101	100	128	149	148	147	146	145	143	142
Vaughan MTS #5 (28kV)	153								64	132	138
Vaughan MTS #6 (28kV)	153					32	31	50	52	68	72
Woodbridge TS (28kV)	80	87	86	79	79	78	78	77	77	76	77
Woodbridge TS (44kV)	80	85	85	86	86	86	87	87	88	90	91
Grand Total		2396	2459	2559	2652	2792	2814	2921	2997	3084	3173

1. Kleinburg 44kV load exceeds LTR between 2023 and 2026. Excess load planned to be transferred to Northern York Region when station is built in 2027.

15 APPENDIX D: ACRONYMS

Acronym	Description
A	Ampere
BES	Bulk Electric System
BPS	Bulk Power System
CDM	Conservation and Demand Management
CEP	Community Energy Plan
CIA	Customer Impact Assessment
CGS	Customer Generating Station
CSS	Customer Switching Station
CTS	Customer Transformer Station
DCF	Discounted Cash Flow
DESN	Dual Element Spot Network
DESIN	Dual Element Spot Network Distributed Generation
DSC	Distributed Ceneration Distribution System Code
GS	Generating Station
GTA	Greater Toronto Area
HV	High Voltage
IESO	
	Independent Electricity System Operator
IRRP	Integrated Regional Resource Plan
kV	Kilovolt
LDC	Local Distribution Company
LP	Local Plan
LTE	Long Term Emergency
LTR	Limited Time Rating
LV	Low Voltage
MEP	Municipal Energy Plan
MTS	Municipal Transformer Station (LDC owned)
MW	Megawatt
MVA	Mega Volt-Ampere
MVAR	Mega Volt-Ampere Reactive
NA	Needs Assessment
NERC	North American Electric Reliability Corporation
NGS	Nuclear Generating Station
NPCC	Northeast Power Coordinating Council Inc.
NUG	Non-Utility Generator
OEB	Ontario Energy Board
OPA	Ontario Power Authority
ORTAC	Ontario Resource and Transmission Assessment Criteria
PEC	Portland Energy Centre
PF	Power Factor
PPWG	Planning Process Working Group
RIP	Regional Infrastructure Plan
RP	Regional Planning
ROW	Right-of-Way
SA	Scoping Assessment
SIA	System Impact Assessment
SPS	Special Protection Scheme
SS	Switching Station
STG	Steam Turbine Generator
TPS	Traction Power Station
TS	Transformer Station
TSC	Transmission System Code
UFLS	Under Frequency Load Shedding
ULTC	Under Load Tap Changer
UVLS	Under Voltage Load Rejection Scheme